

Home Assistant

A setup of Home Assistant with Zigbee2MQTT

- [Installation](#)
- [Zigbee2MQTT setup](#)
- [Home Assistant setup](#)

Installation

This setup assumes, that you have a USB zigbee adapter, that is supported by Zigbee2Mqtt. You can find a list of supported adapters [here](#).

For this guide we will use the [ITEAD Sonoff Zigbee 3.0 USB Dongle Plus V2 model "ZBDongle-E"](#). Make sure to flash it with the coordinator firmware, by following the instructions linked on the Zigbee2Mqtt website.

Pre-Installation

1. Find your Zigbee Adapter. If it is working correctly, it should be available under `/dev/serial/by-id/<device>`, e.g.: `/dev/serial/by-id/usb-ITEAD_SONOFF_Zigbee_3.0_USB_Dongle_Plus_V2_20221101103853-if00`.
2. Create `config/zigbee2mqtt/configuration.yaml` and add the following:

`config/zigbee2mqtt/configuration.yaml`

```
permit_join: true
mqtt:
  base_topic: zigbee2mqtt
  server: mqtt://mqtt:1883
  user: mqtt
  password: <password>
  include_device_information: true
homeassistant: true
serial:
  adapter: ezsp
  port: >-
    <z2m_device>
frontend:
  host: 0.0.0.0
  port: 8090
advanced:
  network_key: GENERATE
  homeassistant_legacy_entity_attributes: false
  legacy_api: false
  legacy_availability_payload: false
```

```
device_options:
  legacy: false
```

Make sure to replace `<z2m-device>` by the path `/dev/serial/by-id/<device>` of your adapter. Also replace the `<password>` by a password of your choice. You will need it later for the homeassistant setup.

3. Create the `docker-compose.yml` file and add the following

`docker-compose.yml`

```
version: '3.8'
services:
  mqtt:
    image: eclipse-mosquitto:2.0
    container_name: mqtt
    restart: unless-stopped
    volumes:
      - "./data/mosquitto:/mosquitto"
    ports:
      - "1883:1883"
      - "9001:9001"
    command: "mosquitto -c /mosquitto-no-auth.conf"

  zigbee2mqtt:
    container_name: zigbee2mqtt
    restart: unless-stopped
    image: koenkk/zigbee2mqtt
    volumes:
      - ./data/zigbee2mqtt:/app/data
      - ./config/zigbee2mqtt/configuration.yaml:/app/data/configuration.yaml
      - /run/udev:/run/udev:ro
    ports:
      - 8090:8080
    environment:
      - TZ=${TZ}
    devices:
      - ${Z2M_DEVICE}:${Z2M_DEVICE}
    labels:
      traefik.enable: true
      traefik.http.routers.z2m.entrypoints: websecure
```

```

    traefik.http.routers.z2m.middlewares: secured@file
    traefik.http.routers.z2m.rule: Host(`z2m.${SITE}`)
    traefik.http.services.z2m.loadbalancer.server.port: 8090
homeassistant:
  container_name: homeassistant
  image: "ghcr.io/home-assistant/home-assistant:stable"
  volumes:
    - ./config/homeassistant:/config
    - /etc/localtime:/etc/localtime:ro
  restart: unless-stopped
  privileged: true
  environment:
    PUID: ${PUID}
    GUID: ${PGID}
  labels:
    traefik.enable: true
    traefik.http.routers.homeassistant.entrypoints: websecure
    traefik.http.routers.homeassistant.rule: Host(`ha.${SITE}`) &&
!Path(`/api/prometheus`)
    traefik.http.services.homeassistant.loadbalancer.server.port: 8123

```

Make sure to add `Z2M_DEVICE=/dev/serial/by-id/<device>` in your `.env`.

4. Start the applications by running `docker compose up -d`

Zigbee2MQTT setup

After you have installed everything as described on the page before, you should be able to reach the zigbee2mqtt frontend on `https://z2m.<site>`.

You can now add devices by searching for the model on the [Zigbee2MQTT Website](#) and following the given instructions.

Note: After you have added all your devices, set `permit_join` to `false` in `config/zigbee2mqtt/configuration.yaml`. If you want to add devices later, you can still do so via the frontend.

Updating devices

You can update the firmware of most of your devices by going to the `OTA` tab on the frontend. This probably takes quite some time and has a tendency to get stuck. If that happens, simply restart the Zigbee2MQTT container and restart the update. It *should* continue where it has last stopped.

Home Assistant setup

You can change a lot of settings in `config/homeassistant/configuration.yaml`. For the beginning it should look something like this:

`config/homeassistant/configuration.yaml`

```
# Loads default set of integrations. Do not remove.
default_config:

# Load frontend themes from the themes folder
frontend:
  themes: !include_dir_merge_named themes

# Text to speech
tts:
  - platform: google_translate

automation: !include automations.yaml
script: !include scripts.yaml
scene: !include scenes.yaml

http:
  server_port: 8123
  ip_ban_enabled: false
  login_attempts_threshold: 3
  use_x_forwarded_for: true
  trusted_proxies:
    - 192.168.0.0/24 # Local Lan
    - 172.42.1.0/24 # Docker network

homeassistant:
  external_url: "https://ha.<SITE>" # note no port number
  internal_url: "http://192.168.0.2:8123" # internal ip address of my HA with port number
```

Make sure to replace your network settings accordingly.

Addind your devices

You can add devices, that you have setup in Zigbee2MQTT by using the [Home Assistant MQTT-Integration](#).

Adding alexa support

Add the following to `config/homeassistant/configuration.yaml`:

```
alexa:  
  smart_home:
```

Then, follow the instructions on the [Home Assistant website](#).